User Manual



Model number: SMPK2077



The MP3 player is a brand-new generation of digital portable device, supporting MP3/WAV music format ,voice recorder, AMV format play ,JPEG photograph browse and E-book text reading .Its perfect sound quality, great reliability and exquisite appearance make it a masterpiece. Devoutly hope to bring you great enjoyment in this digital era.

Unique Features

• Exquisite Appearance

Unique appearance designed and comfortable for handling

• Multi-Codec Player

e.g.: MP1, MP2, MP3, WMA, WMV, ASF and WAV Music format

• Firmware Upgrade

Providing the latest updated features via firmware upgrade from the website (www.curtisint.com)

Drive Free U Disk

You may manage your files directly through "Portable Disk" in "My Computer" on Winows2000 Operating System or above without driver.

• "Private Space" Disk Mode

The flash memory can be divided into two parts by using the accessory tools and one is encrypted to hide the contents saved inaccessible by others. Keep Your Secret!

• Record/ Replay

The player supports recording through built-in microphone and saves as WAV and ACT formats. Meanwhile it supports real digital A-B replay or comparison replay.

7 Preset EQ

Normal, Rock, Pop, Classic, Soft, Jazz and DBB

Multi-play Mode

Normal, Repeat One, Folder, Repeat Folder, Repeat All, Random, Intro.

Power Off

You may set Sleep Timer or Off Time mode in your own convenience.

Declaration

- * Thank you for your purchase.
- * Please read this manual carefully before using your new player.
- * Contents in this manual may change possibly for better service.
- * We have the right to make changes to this manual without notice.

If the actual operations of your player are not the same as the instruction in this manual, please
 visit (www.curtisint.com) for latest product information.


1. Locating the Controls

• Appearance & Keys



S/N	Description	S/N	Description
1	Menu button (Enter/ Return)	6	Power switch
2	Vol/ Hold key(Lock)	7	LCD display
3	Play/Stop	8	USB
4	Previou track/Rewind(৸)/VOL-	9	Earphone head
5	Next track/Forward()→/VOL+		

LCD Window



Battery

The player is in multilevel level battery monitoring system.

Dindicates that battery is 3.6V and the power in battery will become less when using.

EIndicates low battery power and battery should be charged up.

Basic Operation

• Entering Menu System

Pressing **M button** may enter the menu system, including main menu (long press **M button** at Stop state), submenu at Play state (press **M button** to enter) and submenu at stop state (press **M button** to enter).

• Browsing

oBrowsing music files or menu options:

Short press < / > button

oFast forward or fast backward when playing:

Long press < / > button

• Entering Different Modes

You may enter different modes from the main menu.

Main menu:

```
(Long press the \pmb{M}
```

button to enter)

Movie mode:

Music mode: Record mode:

Voice mode:





Photo

System setting

GAME:



Volume Control



Long press *M* button to return to the main menu at the modes. When connecting the USB cable to *PC*, then will enter USB mode.

At the music mode, voice mode, short press **V** buttons to enter the volume control interface and then press the < I > button to adjust volume (follow along with number of volume value be changed).

• Power On/Off

1. Turn on by <u>Power switch</u>

• After push the *Power* switch (OFF→ON) , the player turn on automatically and enter power on *"SYLVANIA"* logo interface:

• When connecting the USB plug to PC, the player turn on automatically and will be entering USB mode:

- 2. Turn ON/Off by <u>Play button</u>, after power switch to ON;
 - when the player is in OFF mode, long press *Play* button to turn on
 - when the player is in ON model ,long press *Play* button to turn off

Play Music

Basic Operation

1. Connect the earphone to the player	2.Turn on "POWER SWITCH"
3. then enter the main menu:	4.press <i>M button</i> to enter the Music mode:
Husic Music Color Co	MP3 d 1 00 128K 002-003 23 ROOT .MP3 0:00:59 1 0:05:33
Short press the PLAY button to play music	 6. Choose music > button : to choose previous music. > button : to choose next music.
 Volume control (Press V) press the < / > button to adjust volume. 	

EQUALIZER Mode

1.When playing music	2.Press the <i>M</i> button to enter Play Submenu
MP3 3 1 0:05:33	
3. select the 'Equalizer' and press MENU	4.choose the EQ that you want from 7 kinds
button to conform.	by press MENU button

• Lyric Display

This player supports "*.LRC" lyric files, and lyrics may be synchronous displayed while playing music.

• How to use lyric files?


Save the lyric file with the same name as that of the corresponding music file.

For example.: Music file name: GiGi-Sky.mp3

Lyric file name: GiGi-Sky.mp3.

• How to know whether the lyrics exist?

If the current song has matching lyric files, the lyric sign in will be display at the top of music mode.



Movie mode

1. Enter the main menu and press the > button to select "MOVIE" mode.



- 2. Press the M to enter.
- 3. press the PLAY to start playing AMV files
- 4. Choose movie

< button : to choose previous file.

> button : to choose next music file.

- 5. Volume control
- 1) Press V
- 2) Press < / > to adjust volume level.

Voice Recording

Make sure that the battery is not in the status of "low battery".


• Recording in Record Mode


1. At the main menu.	2. Press > button to choose recording mode.
Music Music Color	
3. Press <i>M</i> button to enter Record mode	4. Press Play button to start recording.
- WAV	5. Press Play button again to pause recording.
032K 005-004	6.Press Play button to continue recording.
UDICE	7.Long press Play button to stop recording.
REC004 2006/01/01	
0:00:08 567:27:59	

• Select REC type

2. Press <i>M button</i> to enter record subment
4. Press <i>M button</i> enter this option
• REC type:
RAW Fine REC WAV format Fine timbre
- Long REC ACT format Generic timbre
Fine VOR WAV format voice control record
Fine VOR ACT format voice control record

Playback Files





Convert ACT format files to WAV format files

The ACT format files can be converted to WAV format files through the accessory installation tools.

1. Run "Sound Convert Tool" program, and click "Open" button.

🚽 录音转换工具2.0	×
	-
完毕	
tīt -	
转换 帮助 退出	

2. Choose the ACT format files need conversion

打开	<u>?×</u>
查找范围(<u>I</u>):	🕞 录音文件 💽 🗢 🖻 🐨 💷▼
MODO1. ACT MODO2. ACT MODO3. ACT MOD04. ACT MOD05. ACT	
文件名(№):	MODO1.ACT 【打开①
文件类型(<u>T</u>):	Record Files(*.act; *.rcd; *.rec) 💌 取消

4. Click the "Convert" button, the conversion starts

📑 E	8:\1\录音文件\MOD01.wav	x
	► II II III II III 4	
	打开 E:\1\录音文件\MOD01.ACT	
	<u> </u>	

photo

- 1、Entering the main menu.
- 2、Push the ">" buttons to choose "Photo"
- 3、Long press "M" buttons to enter the "Photo"

Besides the conversion from ACT to WAV, the accessory tool can also play WAV and MP3 files.

System Setting

System parameters can be set here and every option varies according to firmware upgrading

At the menu, press > to select the "Setup":



Press *M* button to System Setting interface is as follows:

Clock (Date & time)	set the date and time when recorded files are saved	
LCD set	set the period of time (second) when Backlight stays on without any operation	
Language	Set different language displayed	
Power off	Set a fixed time after which the player may turn power off automatically	
Replay mode	Set working states on Replay mode	
Online device	MTP and USB Disk setting	
Online Mode	an option specially designed for "Private Space" function	
Memory info.	Show memory capacity and percentage that has been used	
Firmware Version	show firmware version	
Firmware	special for firmware upgrading	
Upgrade		
DRM time	Greenwich Mean TIME	
Remove MTP	Exit MTP mode	
info		
Exit	Exit from current interface	

Instruction

"Date & time" set

1. System Setting Interface	2. Press M to enter Record Time Interface.
 Press V to set time in sequence of "YY-MM-DD" 	4. Push < / > button to adjust numbers
5. Press M to confirm and exit.	

\circ "LCD set" setting

Operating steps is as follows:

1. At System Setting interface,	2. Press > key to select "LCD set" option,	

3.	Press M subment		to	enter	"LCD	set"	4.	Press M button to choose 'Brightness screen savers'
5.	Press < / :	> button	to a	adjust	time	Unit	: s	econd), and press M to confirm and exit.

Black screen mode

Set fixed period of time (unit: second) when no operation on keys , the player may turn black screen automatically. If "0" is selected, function is invalid.

• "Language" setting

1. At System setting interface, press < / >	2. Press M button to enter "Language"
button to select "Language" icon:	setting interface:
3. Press < / > button to select desired	
language.	4. Press <i>M</i> to confirm to exit.

Language lists as follows :(maybe add more language)

English
French
German
Italian
Spanish
Portuguese
Dutch
Turkish

• Power saving

Operating steps refer to Language setting.

Off Time mode refers that after a fixed period of time (unit: second) when no operation on keys at Stop mode, the player may turns off automatically to save power. If "0" is selected, power saving function is invalid.

Sleep Time refers that you may set a fixed period of time (unit: minute) for the player to turn off automatically when no keys operation no matter which mode it is at any state. This function is specially designed for listening to music before sleep. *Note:* Setting of Sleep Timer is valid only once and the set time will be cleared after power off. The time needs to be set again next time.

• Replay Mode

Manual Replay means that at A-B Replay Mode the endpoint B can be set manually only.

Auto Replay means that at A-B Replay Mode the endpoint B can be set automatically.

(Especially for English Reading files without music)

• Online Mode

Operating steps refers to Equalizer setting.

Some operating systems (under Windows 2K SP4) can not support two driver letters in one

USB disk. Thus, if "Private Space" function is on, choose which disk you are going to use, i.e.,

"single ordinary disk" or "single encrypted disk", in order for correct display of selected disk after connecting to PC.

• Memory Info.

The number displayed represents total memory capacity and the percentage refers the capacity

used.

Firmware Version

Firmware Version information the player uses can be obtained here.

• Firmware Upgrade


It is specially designed for Firmware Upgrade.

Enter MTP Media

- Choose "Setting" option on the main menu.
 Press < / > to select "Online Device" "Media Device", Press M to confirm
 Connect PC enter into MTP media player
 Pop-up software will show MTP media player, confirm it and choose Sync column

	_	_		
Now Playing 👻 Libi	rary Rip Burn Syn	G Guide	Online Stores	-
Sync "Sync List" to "Al	CIONS MTP DEVICE000001"			
🕑 Start Sync 🛛 📝 Edit	Playlist 📑 Set up Syng		2 📮	
Sync List		~	ACIONS MTP DEVICE000001	
 Title 	Status	Size	Title Size	
	om the list above or click Edit F to create a new list.			

5. Choose the music, and copy into documents file in left column, click"Start Sync"



6. After complete, you can see the music in the right column side.

🕂 Windows Media Player				×
Now Playing 👻 Library	Rip Burn Sync	Guide	Online Stores	
Sync "Sync List" to "ACIONS	MTP DEVICE000001"			
🚯 Start Sync 📝 Edit Play]	.ist 🗟 Set up Syn <u>c</u>		2 🥥	×N
🥏 Items to synchronize		~	ACIONS MTP DEVICE000001	~
Title	Status	Size	∠ Title	Size
⊕ Synchronized to Device (2			■ Wusic ■ Janus Smith ■ Janus Test Content STG1_128_44_16_2_CBR.wm ■ Unknown Artist ■ Unknown Althum STG1_192_44_16_2_CBR.wm STG1_192_44_16_2_CBR.wm	
O Item(s), Total Time: 0:00,	0 bytes		0 bytes / 115.25 MB (114.80 MB	free space)

7. Disconnect USB-cable, the MP3 which inside ID3 Play list with License.

E-Book function

This function supports all TXT file.

1. Enter the main menu.	2. Press > button to choose "E-Book"
-	4.Press > button to select desired text file to read, and then press Play button to enter text interface
5. Press < / > button to turn the pages <i>play</i> ")	s in sequence. (<i>only suitable for "Manual</i>

Game

1. at the main menu



- 2. Press > button to choose "Game" option:
- 3. press *M button* to enter game menu state.
- 4. There are 3 games inside, use < /> to select the games, press M to confirm
- Game 1: RusBlock
 - Press M to start
 - V is down block; M is change direction, long press M return to main menu
 - Play button is Pause; < is left; > is right

Game 2: Puzzle

- Press M to start
- V is up; M is return to main menu;
- < is left; > is right

Game 3: Sudoku


- Press M to start
- V is up and down; Play button is numbering; long press M return to main menu
- < is left; > is right

Note: Long press "V" will lock the player

HOLD

- 1. Long press "V" key to lock (see the picture 1)
- 2. Then continue to long press "V" key to open the lock. (see the picture 2)





Use USB Disk

The player supports standard USB disk function with operating system of Windows98 (driver needed),


Windows 2K and above (driver free), Mac OS 10.3 and above, Linux 2.4.2 and above.

The player supports power supply through USB. At waiting Mode, press **MODE** to exit to main menu, then select to enter desired mode.

The player also supports Suspend Mode.

How to connect to PC? Power on the player and plugs the USB cable to enter the following Mode 1.

The player may display the following mode after connecting to PC:



3.Uploading state:



O **Created new folder** The player can identify the 99 folders set up in the U-disk.

Firmware Upgrade

The player supports firmware upgrading or maintenance through installing special tools on PC.

- 1. Enter the main menu.
- 2. Press > button to select "System Setting"
- 3. Press *M button* to enter System Setting
- 4. Press > button to choose "Firmware upgrade" option
- 5. Press M button to enter "firmware upgrade" interface:
- 6. Connect the player to PC

7. Run the "MP3 Player Update" program in upgrading tools on PC, then click "Select new firmware file" button. the UI is as follows:

🏦 MP3 Player firmware upgradi	ng tool	×			
Device firmware information Device name: S1 Mp3 Player Productor: Wilson Co. Ltd. Version: 3.0.41	Upgraded firmwar Device name: Productor: Version:	e information			
Please select firmware file	Select n	ew firmware file			
	Upgrade log				
HJT490.bin 2004-11-04 12:49 V3.0.41 Success HJT320.bin 2004-11-02 09:45 V3.0.41 Success HJT490.bin 2004-11-04 12:39 V3.0.41 Failed HJT490.bin 2004-11-04 12:39 V3.0.41 Failed HJT490.bin 2004-11-04 12:39 V3.0.41 Failed					
Close	Help				

8. Choose new firmware program (You may find it in accessory CD or download form our website.)

Open				? 🗙
Look in: ा	upgrade	• +	E 💣	·
🖬 HJT490				
File name:				Open
Files of type:	Firmware image file(*.fw;*.bin)		•	Cancel

9、Click "Start" button, the system starts

Device firmware information		Jpgraded firmware information
Device name: S1 Mp3 Playe	ii - 1	Device name: S1 Mp3 Player
Productor: Wilson Co. Ltd.		Productor: Wilson Co. Ltd.
Version: 3.0.41		Version 3041
		Select new firmware file
omplete firmware upgrading		
omplete firmware upgrading		
omplete firmware upgrading		Select new firmware file
	Upgrade I	Select new firmware file
	Upgrade I	Select new firmware file
omplete firmware upgrading 4/1490.bin 2004-11-08 15: 4/1490.bin 2004-11-08 15: 4/1490.bin 2004-11-08 15: 4/1490.bin 2004-11-08 15:	Upgrade 5 V3.0.41 Failed 55 V3.0.41 Failed 55 V3.0.41 Failed	Select new firmware file

10、upgrading.

11、 If upgrading successfully, the player reset.



Provide Strain Notice:

• Firmware upgrade is an operation to promote and optimize the performance of the player. Even if the firmware works without upgrading, there is no any influence on the normal operation of the player.

• Incorrect operation of firmware upgrading may cause the player working abnormally. Please read the manual carefully before operation and firmware upgrading should be operated by the people with basic knowledge in computer operation.

• The upgrading firmware is specially programmed for this player only and not suitable for other serial players, and other firmware is not suitable for this player as well.

Others setting

• Select Folders (At Stop Submenu)

Users can save files in different folders (folders should be created on PC in advance), to manage

and play files according to different types. The player supports identification of 8 level subdirectories.

- 1. At Stop interface. (Current example is at Music MENU, and folders can be selected at both Record and Voice MENU as well.)
- 2. Press *M* to enter Stop Submenu.
- 3. Press **M** again to enter Select Folder interface.
- 4. Press < / > button to select folders at root directory.
- 5. Press PLAY button to confirm and return the stop interface, or short press *M button* to enter next select directories as following view.
- 6. Press < / > **button** to select folders at this directories.
- 7. Press PLAY button to confirm and return the stop interface, or short press *M* button to enter next select subdirectories as following view.
- 8. When did not selected folder as following states.
- 9. Short press **M** button to return previous directory

Note: Independent folders can be set at corresponding mode as Music mode, Record mode and Voice mode, i.e.,

three modes are not bound to correspond with the same folder.

• Delete File (At Stop Submenu)

Files can be deleted at corresponding modes as Music Mode, Voice Mode.

1. At the stop interface.

- 2. Press *M button* to enter stop submenu
- 3. Press > buttons to choose "Delete" option.
- 4. Press *M button* to enter Delete file folder
- 5. Press *M button* to enter Delete file folder submenu
- 6. Press > button to choose "Delete" or "Delete all", and Press *M button* to confirm and deletion starts.

Remark: "Delete All" means to delete all the relevant files at current mode in current folder. (For example,

at Music Mode executing "Delete All", all the music files in current files may be deleted, while recorded files

without change.)

Note: When deleting files on PC, please take care to eject the player safely before pulling out USB cable, otherwise files may not be deleted.

• Play Mode (Play Submenu)

When playing music and recorded files, different play modes can be selected.

Enter play/stop submenu to enter

The first option in Play Submenu is Play Mode. The player will play files according to the mode selected.

📆 Normal	Play files in current folder in normal sequence and then play other files in next folders one by one
📆 Repeat One	Play a single music file repeatedly
🐻 Folder	Play all music files in current folder in sequence and stop
ቼ Folder All	Play all music files in current folder repeatedly
😤 Repeat All	Play all music files repeatedly
🛃 Random	Play music files in current folder randomly
🚼 Intro	Play the first 10 seconds of each music file in sequence in the current folder

• Tempo Rate (Play Submenu)

When playing music(Only for MP3 formats) or recorded files, different tempo rate can be set (faster or slower) without changing the tone and sound. Files.

- 1. When playing music
- 2. Press **M** button to enter Play Submenu is as follows:
- 3. Press > button to choose Tempo Rate option
- 4. Press **M** button to enter Tempo Rate interface is as follows:

5.Press > button to quicken tempo rate and press < button to slow down tempo rate.

Replay Mode

○ A-B Replay

- 1. At Music Mode or Voice Mode
- 2. Press *M* to enter Play Submenu.

- 3. Press > to select "Replay".
- 4. Press *M* to enter Replay.

"A" flickers in Replay Mode icon 💼 and start point is to be set.

- 5. Press > to set "A".
- 6. After "A" set, "B" flickers in icon 📩, and endpoint B needs to be set.
- 7. Press > to set "B".

Replay icon is fixed and A-B segment replay begins. When replay times count up to times set in advance, the player will quit from Replay Mode. At Replay Mode, pressing < can set "A" again to select another segment. (Setting of replay times refers to "Replay Times" in the > section.

• Replay Times (Play Submenu)

Operating steps refer to Backlight setting.

Replay times mean that after A-B segment has been replayed up to fixed times; it will exit from

Replay Mode.

• Replay Gap (Play Submenu)

Operating steps refer to Backlight setting.

Replay gap means the break period between different playing times (unit: second).

AMV Convert Tool operation introduce

This tool used for transforming the media files to the AMV file\

1、Run the software can pass to click the "AMV Convert Tool", click the "Software, after running the software,

can pass to click the

add file button to add the media file.

2、After choose unsettled AMV files, click the "button, then click " output information" column set button enters ,choose AMV files high & length is 128*128.

- 3、licks directly button and tool will begin convert be selected file, as follows chart:
- 3、 After convert completes, the AMV Player will play AMV file automatically.

Trouble Shooting

	*	Check whether Volume is set "0" and connect the headphone plugs
		firmly.
No sound is heard from headphone.	资	Check whether the headphone plug is dirty.
	発	Corrupted MP3 may make a static noise and the sound may cut off.
		Make sure that the music files are not corrupted.
Characters in LCD are corrupted	*	Check whether the right language has been selected.
	発	Check whether USB cable is damaged and is connected properly.
Download of music files fails.	発	Check whether driver is installed correctly.
	*	Check whether the player's memory is full.

Specifications

Dimension	70*52*8mm			
Weight	48g			
LCM Window	1.8"			
PC connection	USB2.0(FS) (Read: 1000K Byte, Write: 1000-900K Byte)			
Flash memory	2GB			
Battery	300mA			
Battery	Max Play time: 6-7 hours			
	Sample rate	8KHz		
Record	Recording format	ACT, MP3		
	Recording time	35hours (ACT, 128M Flash)		
	Max output of	(L) 10mW+ (R) 10mW (32 Ohm)		
	headphone			
MP3、WMA、ASF	MP3 bit rate	8K bps – 320K bps		
	WMA、WMV bit rate	5K bps – 384K bps		
	Frequency response	20Hz to 20KHz		
	SNR	85dB		
Music format	MP1、MP2、MP3、WMA			
Working temperature	-5 to 40			
Operating System	Windows98/SE/ME/2K/XP、Mac OS 10、Linux 2.4.2			